

## KR024

1 Fazlı 7 Kademeli Şalter  
1 phase 7 Ways Switch



| KR024 1 FAZLI 7 KADEMELİ ŞALTER          |               | 1 | 3 | 5 | 7 | 9  | 11 | 13 |
|--|---------------|---|---|---|---|----|----|----|
| ÜRETİM PROGRAMI                          | ŞALTER KONUMU | 1 | 5 | 2 | 6 | 3  | 7  | 4  |
|  |               | 2 | 4 | 6 | 8 | 10 | 12 | 14 |
| K2 16A,25A<br>K3 40A,63A<br>K4 100A,125A | 0             |   |   |   |   |    |    |    |
|  | 1             | X |   |   |   |    |    |    |
|  | 2             |   |   | X |   |    |    |    |
|  | 3             |   |   |   |   | X  |    |    |
|  | 4             |   |   |   |   |    |    | X  |
|  | 5             |   | X |   |   |    |    |    |
|  | 6             |   |   |   | X |    |    |    |
|  | 7             |   |   |   |   |    | X  |    |

| Anma akımı<br>Rated current | Boyut<br>Size | Koli ölçüleri<br>Box sizes |
|-----------------------------|---------------|----------------------------|
| 16 A                        | K2            | 70x70x130                  |
| 25 A                        | K2            | 70x70x130                  |
| 40 A                        | K3            | 90x90x180                  |
| 63 A                        | K3            | 90x90x180                  |
| 100 A                       | K4            | 90x90x210                  |
| 125 A                       | K4            | 90x90x210                  |